


Air Purifier

Thank you for purchasing our products
Please read the instruction carefully before use
Please keep the instruction manual properly

Product Parameters

- 1 . Product name : FRESHR Air Purifier
- 2 Product model : GXZ-AP01
- 3 . Material ABS / Filter / PCBA
- 4 . Battery Voltage : 3.7V
- 5 . Battery Capacity : 10000mAh
- 6 . Battery Power : 37Wh
- 7 . Input Voltage / Current : DC5 0V / 1500mA(±20%);
- 8 . Fan working current : 1st speed / 300mA; 2nd speed / 595mA;
- 3rd speed / 1190MÁ (±10%);
- 9 . Fan working power : 1st speed / 1.15W; 2nd speed / 2.2W;
 - 3rdspeed / 4.5W;
- 10 . Anion concentration : 8 * 10⁸PCS/cm³ (distance the emitter from 10 cm test.)
- 11 . PPM : < 0.05PPM
- 12 . Product size : 160 * 160 * 268mm
- 13 . Product weight : 1.25kg 14 . Executive standard : GB4706.45-2008
- 15 . Inspection : Qualified
- 16 . Place of orgin : Shenzhen,China

Product Pa



ction Operation

- 1.Button "M" function: Press "M" button once, start the Auto Mode. Fan will switch to gear according to Air quality. Press "M" button twice, for manual mode 1 gear. Press "M" button third time, shift manual mode to 2 gears. Press "M" button fourth time, shift manual mode to 3 gears. Press "M" button fifth time turn off the product.
- 2. Anion function: Long press "M" button once, start the anion, long press "M" button twice, turn it off.
- 3.Night Mode: Double press "M" button once, turn on the night light;

 Double press "M" button twice, turn it off
- 4.Type-C interface : The charge port can be charging as power supply.
- 4. Type-C interface: The charge port can be charging as power supply.

 5. Power off switch: Place the outage switch shift to "ON" and connecting
- Notice: Anion function can be working in

any status as well as controlled turn on or off separately in any conditions.

the power source, place it to "OFF" and turn power source off.

LED Panel

- 1.Air quality light color: The air quality indicates on "RED" , means the air quality is very bad, the air quality indicates on "YELLOW" , means the air quality is poor, the air quality indicates on "Green" , means air quality is good.
- 2.Air quality indicator: during the product connect to power source, after LED Panel gets initializing, air quality light indicates on Green, after warm up 3 mins which the product transfers to indicator light color according air quality.
 3.Anion indicator: start the anion, light indicate on Green, flash, when turn it off.
- nion indicator : start the anion, light indicate on Green, flash, when tu light indicates on RED and put out.
- 4.Work instruction: When automatically mode direct to "AUTO" fan indicates on 1-2-3 according to air quality changes. Thebutton whitebackground for breath light; when manual mode direct to "MANU", fan 1 gear indicates on 1,fan 2 gears indicates on 2,fan indicates on 3rd(when it is under all manual mode on condition, the button white background for lasting light); when turn off function, all indicator light put out.
- S.Battery indicator: when charging, battery is changing from 0-100%.100% isfull battery.
 6.Low battery: when battery under 10%, digital 10 flicker till power off. Reboot it to start the function, digital 0 flickers 10 times till power off.
- Notice: When working in all modes, the fan working display flashes and the negative ion display flashes.

Battery Using Time

- 1. Charging current: 1500mA (20%), full battery approx 7 hrs.
- 2.1st gear working 32 hrs,2nd gear working 15 hrs, 3rd working 7 hrs.
- 3.Please first charge the product for more than 3 hours before use.
- 4. It is recommended to charge the product a time per 3 months in case of battery damage and unserviceable.
- 5. When the product is not working for a long time, please make sure it can storage under low humidity or room temperature in case of environment factors to the product function damage.

Attentions

- 1.It is recommended to do a clean once in half month to the product, which replaced the filter per 3 months.
- Prohibited wash filter with water. Please aim the hairdryer directly to HEAP
 core inside blow more times, or with soft brush, toothbrush cleans up the dust
 which attached the filter net around.
- 3. Please DO NOT knock it purposely when you clean filter core to ward off the filter core construction damages that cannot be filtering effect.
- 4.The product is apply to 10-20 square meters. If room space exceed this range please select the proper product.
- 5.The product working will come about slight ozone, please turn the product off and open the window and ventilate if you feel uncomfortable to the body.
- Please DO NOT spray essence, essential oil, perfume etc. corrosive liquid to the filter.

Filter element replacement steps









tighten the host

Product Accessories :

to open the host

 $Air\ purifier *1pc, Tpye-c\ cable *1pc, User\ manual *1pc, Qualified\ certificate *1pc, Constraint *1pc, C$